

# ACCENTRONIX

## Gallagher

### Commands and Reporting Setup

#### Setup

- Connect the Cellswitch to the Gallagher energizer by using the splitter block and convertor.
- Cellswitch is powered directly by the Gallagher Energizer through the converter from the LCD keypad cable. No other connection to Cellswitch required.
- Apply power to the Energizer and wait one minute for the GREEN LED on the Cellswitch to start to flash slowly.
- Register the Cellswitch on [www.cellswitchportal.co.za](http://www.cellswitchportal.co.za)
- Select the 'Gallagher' option in the General Setup in Advanced Options.
- Add your own mobile number in the 'Access Control' section and click on the "enable alerts" checkbox.
- Click on 'Update' on the top of the screen and wait one minute for the GREEN LED on the Cellswitch to start to flash slowly.
- Install the Accentronix Smart Home app on your phone from the Play Store.
- Click on the app buttons to control the device.
- You will receive a status message from the energizer on the Accentronix Messenger app. If the Messenger app is not installed on your phone, you will receive the messages by SMS.

#### SMS Command Examples

- On - Switch energizer on
- Off - Switch energizer off
- ? - Energizer Status
- ?? - Current configurations settings
- KVout=4.5# - Set output voltage - Range: 4.5, 5.5, 6.5, 8.0
- KValarm=4.5# - Set voltage alarm trigger - Range: 4.5 to 8.0
- Ialarm=5# - Set current alarm trigger - Range: 5 to 199
- Ealarm=0.5# - Set earth/ground alarm trigger - Range: 0.5 to 2.0



# Connection diagram



## NOTE:

- The Cellswitch is powered directly by the Gallagher Energizer through the converter from the LCD keypad cable. No other connections to the Cellswitch are required.
- The zones are automatically detected by the Cellswitch.

## Get in Touch

Office and Technical: +27 87 550 3479

Technical support Whatsapp line: +27 63 631 0314

[www.accentronix.co.za](http://www.accentronix.co.za)

